

<div><div><div>hasivo®</div></div><div>Hardware specifications</div></div>	
Model	G1200W-8G-2TS-PRO
Product name	Industrial 2+8 Full Gigabit Managed Switch
Fixed Port	8*10/100/1000M Rj45 2*10/100/1000M Uplink Rj45 2*1000M SFP
Console Port	1
Reset Key	1
FLASH	16M
RAM	128M
Bandwidth	56Gbps
Packet Forwarding	14.44Mpps
MAC	8K
Buffer	4.1M
Transmission Distance	10BASE-T : Cat3,4,5 UTP(=250 meter) 100BASE-TX : Cat5 or later UTP(150 meter) 1000BASE-TX : Cat6 or later UTP(150 meter) SFP: 1000M single and multimode optical module with maximumdistance =120km (depending on the optical module)
LED Indicator	9-10:(SFP LED) Port1-8:(Green=100M; Green+Orange=1000M) PWR:(Power/system LED) V1:(Main power indicator light) V2:(From the power indicator light) HW:(Ring network ON LED)
Watt	Standby power consumption≤ 5W; Network Full-load power consumption≤15W;
Power Input	2 group of independent power input SW:DC12-57V
Lightning Protection Level	6KV 8/20us; 8KV ESD IP40
Storage Temperature/ Humidity	-40~+80°C;10%~90% RH No coagulation
Operating Temperature/ Humidity	-40~+85°C;5%~95% RHR No coagulation
Product size/Packing size(L*W*H)	160mm*130mm*45mm 280mm*165mm*79mm
N.W/G.W(kg)	1.1kg/1.3kg
Installation	DIN guide rail type(additional wall hangers)
Certificate	3C; CE mark, commercial; CE/LVD EN60950; FCC Part 15 Class B; RoHS;
Warranty	Whole device for 1 year(Accessories not included)

The data presented above represents the performance of the product in specific equipment and experimental environments. Based on the actual on-site environment or differences in equipment, there may be differences. The technical comparisons mentioned are based on scientific principles and do not involve other purposes

Due to real-time changes in product version, batch, and production supply factors, in order to provide as accurate product information and functional parameters as possible, Hasivo may adjust the content on the above pages in real time to ensure consistency with the actual product. Any adjustments are subject to no further notice. Due to factors such as measurement environment and method, there may be certain scientific errors in product dimensions, parameters, and other information.