

## UPKTECH BN-L-TN PCB NG/OK Buffer Conveyor

### I. Introduction

SMT PCB NG/OK Buffer - the perfect solution for electronics manufacturers who require a reliable, efficient, and easy-to-use buffer system for their production line. With the ability to sort and store NG and OK PCBs separately, this buffer helps streamline the assembly process and prevent errors.



### II. Product features

1. Strong, firm and stable design
2. User friendly 'soft touch' LED membrane control panel or touch screen can be selected.
3. Top&bottom pneumatic clamps to secure magazine rack
4. No PCB breakage guaranty because of special gas circuit design
5. Automatic detection of fault code display function
6. Wear-resistant cable and have long service life
7. SMEMA compatible

### III. Specification

Technical Parameters	
Description	This unit is used for automatic loading operation of double-side boards and transceiver board
PCB size	50*80-330*250-530*460
No.of magazine	Upper conveyor :1 magazine lower conveyor :1 magazine
Magazine replacement time	Approx.30 seconds or specify
Indexing pitch	10.20.30.40mm or specify
Power supply	AC1P110V/220V

<b>Power</b>	Max 300VA
<b>Air pressure</b>	4-6bar,10ltr/min max
<b>Transport height</b>	900±20mm(Or customized)
<b>Transport direction</b>	From left to right or right to left

#### IV. Operation diagram

