

# ETMY ET-77

## Professional Walkie-talkie



Built in Flashlight



FM radio function

One-button alarm

FM radio Function

VOX Function



## Parameters



### Main functions

- Flashlight
- Channel Monitor
- Busy Channel Lockout(BCL)
- Voice Operated Transmitting(VOX)
- Emergency alert
- Time-out Timer (TOT)

### General

Frequency Range	UHF: 400 ~ 470MHz
Memory Channel	16
Battery Capacity	1500mAh
Frequency Stability	±2.5ppm
Operating Temperature	-20℃~ +50℃
Operating Voltage	DC 3.7V
Dimension	116 × 57 × 35 mm (Not including antenna)
Weight	180g (Including antenna and battery)


### Transmission part

Output power	≤5W
Modulation	F3E
Maximum frequency offset	≤1KHz / ≤2.5KHz
Spurious emission	±7.5μW
Adjacent power	≤ -65dB / ≤-60dB
SIGNAL-NOISE RATIO	≤ -40dB / ≤-35dB
CTCSS	0.7±0.1KHz / 0.4±0.1KHz
Modulation sensitivity	8-12mV
Emission current	±1.4A

### Receiving part

Receiving sensitivity	< 0.16μV
Squelch sensitivity	< 0.2μV
Audio power	0.5W
Audio distortion	<10%
Sinal imitation	≥65dB
Intermediation(wide/narrow)	≥65dB / ≥60dB
Adjacent channel selectivity(wide/narrow)	≥65dB / ≥60dB


### Standard Accessories




Back clip



Antenna



Battery



Charger



Manual



Scan for more of our products