Wired Condenser Microphone [Choir Microphone]

VM-HD828



Functional description :

1. The large-diaphragm condenser microphone features a cardioid pattern, making it suitable for studio recording and live performances.
2. Utilizes a gold-plated diaphragm;

Technical specifications:

Polar Pattern	Cardioid
Sensitivity (at 1000Hz)	-32dBV ±2dB (25mV/Pa)
Frequency Range	80 – 20,000 Hz
Output Impedance	200 Ω
Pad (Attenuation)	-10 dB
Equivalent Noise Level (A-weighted)	25 dB
Signal-to-Noise Ratio	80 dB
Maximum SPL	200 dB (1kHz, THD ≤1%)
Power Supply	48V Phantom Power