



DIGITAL THERMOMETER

Product specifications

Temperature measurement range: $-50^{\circ}\text{C} \sim +70^{\circ}\text{C}$ ($-58^{\circ}\text{F} \sim +158^{\circ}\text{F}$)

Temperature measurement accuracy: $\pm 1^{\circ}\text{C}$ (1.8°F)

Temperature resolution: 0.1

Power supply: LR44


Basic functions

MAX/MIN memory


Temperature display

$^{\circ}\text{C}/^{\circ}\text{F}$ temperature switch

Operation method



- ◇ Hold (①) key 1.5 seconds to power ON/OFF
- ◇ Double click (①) key to select the temperature unit: $^{\circ}\text{C}$ or $^{\circ}\text{F}$
- ◇ Click (②) key check the MAX/MIN recorded
- ◇ On the Max/Min mode, hold (②) key 1.5 seconds to clear record



- ◇ With back hole (suction cup) for wall mounting indoor and outdoor
- ◇ Battery cover, unscrew to open the cover to replace the battery